

E-FSA64 and E-FSA250 Compatibility List

Subassemblies

Manufacturer	Model	Description	Installation sheet
Edwards	D16L-Fa	16-zone LED display expander	3101204
	SA-232	RS-232 interface card	3101095
	SA-CLA	Class A interface card	3101094
	SA-DACT	Dialer	3101099
	SA-ETH	Ethernet interface card	3101100
	XAL127	Loop expander card (eFSA250 and FX-254 panels only)	3101093

Addressable detectors

Manufacturer	Model	Description
Edwards	E-PD	E series photoelectric smoke detector
	FX-PD	FX series photoelectric smoke detector
	E-PHD	E series combination photoelectric smoke/fixed-temperature heat detector
	FX-PHD	FX series combination photoelectric smoke/fixed-temperature heat detector
	E-HD	E series combination fixed temperature/rate-of-rise heat detector
	FX-HD	FX series combination fixed temperature/rate-of-rise heat detector
	E-PDD	E series duct smoke detector
	FX-PDD	FX series photoelectric duct smoke detector

Addressable modules

Manufacturer	Model	Description
Edwards	E-270	E series single-action fire alarm station, English markings, metal
	FX-270	FX series single-action fire alarm station, English markings, metal
	E-278	E series double-action, single-stage fire alarm station, plastic
	FX-278	FX series double-action, single-stage fire alarm station, plastic
	E-IDC1A	E series Class A single input module
	FX-IDC1A	FX series Class A single input module
	E-IDC1B	E series Class B single input mini module

Manufacturer	Model	Description
	FX-IDC1B	FX series Class B single input mini module
	E-2WIRE	E series Class A/B two-wire smoke module
	FX-2WIRE	FX series Class A/B two-wire smoke module
	E-IDC2B	E series Class B dual input module
	FX-IDC2B	FX series Class B dual input module
	E-IDCWS	E series combination waterflow/supervisory module
	FX-IDCWS	FX series combination waterflow/supervisory module
	E-NAC	E series NAC module
	FX-NAC	FX series NAC module
	E-RLY	E series control relay module
	FX-RLY	FX series control relay module
	E-ISO	E series SLC fault isolator module
	FX-ISO	FX series SLC fault isolator module

E-2WIRE and FX-2WIRE (ID 1.0) smoke detectors [1] [2]

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC
Edwards	2M-PD	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	30
	2M-PDC	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	30
	2M-PDHC	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/RoR)	S10A / N/A	N/A	30
	2M-PDHRC	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual FT/RoR heat sensor, and auxiliary relay	S11A / N/A	N/A	1
	2420	Ionization smoke detector	100 / N/A	N/A	60
	2430	Photoelectric smoke detector	100 / N/A	N/A	46
	2432B	Combination photoelectric smoke/heat detector	100 / N/A	N/A	46
	2435P	Photoelectric duct smoke detector	100 / N/A	Included	46
	429C	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	30
	429CRT	Photoelectric smoke detector (12/24 VDC) with dual heat sensor (FT/RoR) and auxiliary relay	S11A / N/A	N/A	1
	429CST	Photoelectric smoke detector (12/24 VDC) with dual heat sensor (FT/RoR) and sounder	S11A / N/A	N/A	1
	429CT	Photoelectric smoke detector (12/24 VDC) with dual heat sensor (FT/RoR)	S10A / N/A	N/A	30
	511C	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	30
	521B	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	30

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC
	521BXT	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/RoR)	S10A / N/A	N/A	30
	521NB	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	10
	521NBXT	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/RoR)	S10A / N/A	N/A	10
	521CRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/RoR), and auxiliary relay	S11A / N/A	N/A	1
	521NCRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/RoR), and auxiliary relay	S11A / N/A	N/A	1
	521NCSRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/RoR), auxiliary relay, and sounder	S11A / N/A	N/A	1
	521NCSXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual heat sensor (FT/RoR), and sounder	S10A / N/A	N/A	30
	528B	Photoelectric smoke detector (12/24 VDC) with CleanMe	N/A / N/A	N/A	30
	528BXT	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/RoR)	N/A / N/A	N/A	30
	528CRXT	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual FT/RoR heat sensor, and auxiliary relay	N/A / N/A	N/A	1
	6249B	Ionization smoke detector and base	001 / N/A	N/A	45
	6249C	Ionization smoke detector and base	N/A / N/A	N/A	45
	6250B	Ionization smoke detector	001 / 001	6249B-001 6251B-001A	45
	6250C	Ionization smoke detector	N/A / N/A	6249B-001 6251B-001A	45
	6264B-001 [3]	Ionization duct smoke detector	001 / 001	6251B-001A	45
	6264C-001 [3]	Ionization duct smoke detector	001 / 001	6251B-001A	45
	6266B-001 [3]	Photoelectric duct smoke detector	001 / 001	6251B-001A	24
	6266C-001 [3]	Photoelectric duct smoke detector	001 / 001	6251B-001A	24
	6269B	Photoelectric smoke detector and base	001 / N/A	N/A	24
	6269B-003	Photoelectric smoke/heat detector and base	001 / N/A	N/A	21
	6269C	Photoelectric smoke detector and base	N/A / N/A	N/A	24
	6269C-003	Photoelectric smoke/heat detector and base	N/A / N/A	N/A	21
	6270B	Photoelectric smoke detector	001 / 001	6249B-001 6251B-001A	21
	6270B-003	Combination photoelectric smoke/heat detector	001 / 001	6249B-001 6251B-001A	21
	6270C	Photoelectric smoke detector	N/A / 001	6249B-001 6251B-001A	21

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC
	6270C-003	Combination photoelectric smoke/heat detector	N/A / 001	6249B-001 6251B-001A	21
	711U	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	701U, 702E, 702U	30
	711UT	Fast response photoelectric smoke detector (12/24 VDC) with heat sensors	S10A / N/A	701U, 702E, 702U	30
	713-5U	Two-wire rate-of-rise and 57°C (135°F) fixed temperature heat detector	S10A / S00	701U, 702E, 702U	10
	721UT	Fast response photoelectric smoke detector (12/24 VDC) with remote alarm/trouble LED	S10A / N/A	701U, 702E, 702U	30
	731U	Photoelectric smoke detector (12/24 VDC) with auxiliary relay	S11A / N/A	701U, 702E, 702U	1
	C2M-PD	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	30
	C2M-PDC	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	30
	C2M-PDHC	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/RoR)	S10A / N/A	N/A	30
	C2M-PDHRC	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual FT/RoR heat sensor, and auxiliary relay	S11A / N/A	N/A	1
	EC10U-3 [5]	Ionization smoke detector	A / A	CSBU-1, CSBU-3, CSB4U-1	46
	EC20FTU-3	Fixed temperature heat detector, 135°F (58°C)	A / A	CSBU-1, CSBU-3, CSB4U-1	46
	EC20RRU-3	Rate of rise heat detector, 135°F (58°C)	A / A	CSBU-1, CSBU-3, CSB4U-1	46
	EC30U-3 [5]	Photoelectric smoke detector	A / A	CSBU-1, CSBU-3, CSB4U-1	48
	EC30DU-3 [6]	Photoelectric duct smoke detector	A / A	CSBU-1, CSBU-3	16
	ED2M-PD	Photoelectric smoke detector (12/24 VDC)	S10A / N/A	N/A	30
	ED2M-PDC	Photoelectric smoke detector (12/24 VDC) with CleanMe	S10A / N/A	N/A	30
	ED2M-PDHC	Photoelectric smoke detector (12/24 VDC) with CleanMe and dual heat sensor (FT/RoR)	S10A / N/A	N/A	30
	ED2M-PDHRC	Photoelectric smoke detector (8.5 to 33 VDC) with CleanMe, dual FT/RoR heat sensor, and auxiliary relay	S11A / N/A	N/A	1
	EDW1151A	Ionization smoke detector	N/A / N/A	EDWB110LP	24
	EDW1400A	Ionization smoke detector	N/A / N/A	N/A	24
	EDW1451A	Photoelectric smoke detector	N/A / N/A	EDWB401B	24
	EDW2151A	Photoelectric smoke detector	N/A / N/A	EDWB110LP	24
	EDW2451A	Photoelectric smoke detector	N/A / N/A	EDWB401B	24
	SD-2W [4]	SuperDuct photoelectric duct smoke detector	0.0 / N/A	N/A	42
	SC10U-3 [5]	Ionization smoke detector	A / A	CSBU-1, CSBU-3, CSB4U-1	46

Manufacturer	Model	Description	UL ID	Compatible base	Max. per IDC
	SC20FTU-3	Fixed temperature heat detector, 135°F (58°C)	A / A	CSBU-1, CSBU-3, CSB4U-1	46
	SC20RRU-3	Rate of rise heat detector, 135°F (58 °C)	A / A	CSBU-1, CSBU-3, CSB4U-1	46
	SC30U-3 [5]	Photoelectric smoke detector	A / A	CSBU-1, CSBU-3, CSB4U-1	48
	TS7-2	Photoelectric smoke detector (12/24 VDC) and base	S10A / N/A	N/A	30
	TS7-2R	Photoelectric smoke detector (12/24 VDC) with auxiliary relay and base	S11A / N/A	N/A	1
	TS7-2T	Fast response photoelectric smoke detector (12/24 VDC) with remote alarm/trouble LED and base	S10A / N/A	N/A	30
	FX7-2	Photoelectric smoke detector and base	S10A / N/A	N/A	30
	FX7-2R	Photoelectric smoke detector, base, and auxiliary relay	S11A / N/A	N/A	1
	FX7-2T	Photoelectric smoke detector and base, RoR heat detector, remote test, alarm/trouble LED output	S10A / N/A	N/A	30

[1] Do not install different smoke detector models on the same circuit

[2] Do not install dry contact devices on the same circuit as smoke detectors if the circuit is configured for alarm verification

[3] Requires a compatible base and 6260A-100 housing

[4] Do not install on circuits configured for alarm verification

[5] Do not install on circuits configured for alarm verification unless installed in a resistor base

[6] Requires a compatible base and 6260A-CU housing

Notification appliances

Manufacturer	Model	Description	Audible sync	Visible sync
Edwards	202-3A-T, 202-3A-TW, 202-5A-T, 202-5A-TW, 202-6A-T, 202-6A-TW, 202-7A-T, 202-7A-TW, 202-8A-T, 202-8A-TW, MS-3AR, MS-3AW, MS-5AR, MS-5AW, MS-6AR, MS-6AW, MS-7AR, MS-7AW, MS-8AR, MS-8AW	Integrity synchronized strobes	N/A	Y
	202-15PS, 202-15PSW, 202-75PS, 202-75PSW	Power saver synchronized strobes	N/A	Y
	405-3A-T, 405-3A-TW, 405-5A-T, 405-5A-TW, 405-6A-T, 405-6A-TW, 405-7A-T, 405-7A-TW, 405-8A-T, 405-8A-TW, 4MS-3AR, 4MS-3AW, 4MS-5AR, 4MS-5AW, 4MS-6AR, 4MS-6AW, 4MS-7AR, 4MS-7AW, 4MS-8AR, 4MS-8AW, CS405-7A-T, CS405-8A-T	Integrity synchronized strobes	N/A	Y
	405-15PS, 405-15PSW, 405-75PS, 405-75PSW	Power saver synchronized strobes	N/A	Y
	757-1A-C, 757-1A-CW	Integrity chimes	N/A	N/A
	757-3A-CS, 757-3A-CSW, 757-5A-CS, 757-5A-CSW, 757-7A-CS, 757-7A-CSW, 757-8A-CS, 757-8A-CSW	Integrity synchronized chime/strobes	N/A	Y
	757-1A-T, 757-1A-TW, INT-T, INT-TW	Integrity synchronized temporal horn	Y	N/A
	757-3A-T, 757-3A-TW, 757-5A-T, 757-5A-TW, 757-7A-T, 757-7A-TW, 757-8A-T, 757-8A-TW, INT-3AT, INT-3ATW, INT-5AT, INT-5ATW, INT-7AT, INT-7ATW, INT-8AT, INT-8ATW	Integrity synchronized temporal horn/strobes	Y	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	757-1A-H, 757-1A-HW	Horns	N	N/A
	757H-15PS, 757H-15PSW, 757H-75PS, 757H-75PSW	Power saver synchronized temporal horn/strobes	Y	Y
	2440S-15-R, 2440S-15-W, 2440S-30-R, 2440S-30-W, 2440S-60-R, 2440S-60-W, 2440S-15/75-R, 2440S-15/75-W, 2440S-110-R, 2440S-110-W	Integrity synchronized strobes	N/A	Y
	2441S-15-R, 2441S-15-W, 2441S-30-R, 2441S-30-W, 2441S-60-R, 2441S-60-W, 2441S-15/75-R, 2441S-15/75-W, 2441S-110-R, 2441S-110-W	Integrity synchronized strobes	N/A	Y
	2447TH-R	Horns	Y	N/A
	2452THS-15, 2452THS-15/75, 2452THS-30, 2452THS-15/75, 2452THS-110	Horn/strobes	Y	Y
	2455C-R, 2455C-W	Integrity chimes	N/A	N/A
	2457CS-15-R, 2457CS-15-W, 2457CS-30-R, 2457CS-30-W, 2457CS-15/75-R, 2457CS-15/75-W, 2457CS-110-R, 2457CS-110-W	Integrity synchronized chime/strobes	N/A	Y
	EG1-HD, EG1R-HD, EG1F-HD, EG1RF-HD, G1-HD, G1R-HD, G1F-HD, G1RF-HD, MG1-HD, MG1R-HD, MG1F-HD, MG1RF-HD	Genesis temporal horns	Y	N/A
	EG1-HDVM, EG1R-HDVM, EG1F-HDVM, EG1RF-HDVM, G1-HDVM, G1R-HDVM, G1F-HDVM, G1RF-HDVM, MG1-HDVM, MG1R-HDVM, MG1F-HDVM, MG1RF-HDVM	Genesis temporal horn/strobes, 15 to 110 cd	Y	Y
	EG1-VM-A, G1-VM-A, MG1-VM-A	Genesis strobe, 15 to 110 cd, selectable lenses	N/A	Y
	EG1-VM-RCC, G1-VM-RCC, MG1-VM-RCC	Genesis strobe, ceiling mount, 15 to 110 cd, private mode only	N/A	Y
	EG1-HDVM-A, G1-HDVM-A, MG1-HDVM-A	Genesis temporal horn/strobe, 15 to 110 cd, selectable lenses	Y	Y
	EG1-HDVM-RCC, G1-HDVM-RCC, MG1-HDVM-RCC	Genesis temporal horn/strobe, ceiling mount 15 to 110 cd, private mode only	Y	Y
	EG1F-V1575, EG1RF-V1575, MG1F-V1575, MG1RF-V1575, G1FV1575	Genesis strobe, 15 or 75 cd	N/A	Y
	EG1F-CV1575, G1F-CV1575, MG1F-CV1575	Genesis chime/strobe, low or high dbA, 15 or 75 cd	N/A	Y
	EG1F-HDV1575, EG1RF-HDV1575, G1F-HDV1575, MG1F-HDV1575, MG1RF-HDV1575	Genesis temporal horn/strobe, low or high dbA, 15 or 75 cd	Y	Y
	EG1R-VM-RCW, G1R-VM-RCW, MG1R-VM-RCW	Genesis strobe, wall mount, 15 to 110 cd, private mode only	N/A	Y
	EG1R-HDVM-RCW, G1R-HDVM-RCW, MG1R-HDVM-RCW	Genesis temporal horn/strobe, wall mount 15 to 110 cd, private mode only	Y	Y
	EG1-H, EG1R-H, EG1-HO, EG1R-HO, EG1F-HO, EG1RF-HO, G1-H, G1R-H, G1-HO, G1R-HO, G1F-HO, G1RF-HO, MG1-H, MG1R-H, MG1-HO, MG1R-HO, MG1F-HO, MG1RF-HO	Genesis temporal horns	Y	N
	EG1-V15, EG1R-V15, EG1F-V15, EG1RF-V15, G1-V15, G1R-V15, G1F-V15, G1RF-V15, MG1-V15, MG1R-V15, MG1F-V15, MG1RF-V15, EG1-V15	Genesis strobes, 15 cd	N/A	Y

Manufacturer	Model	Description	Audible sync	Visible sync
	EG1-V30, EG1R-V30, EG1F-V30, EG1RF-V30, G1-V30, G1R-V30, G1F-V30, G1RF-V30, MG1-V30, MG1R-V30, MG1F-V30, MG1RF-V30	Genesis strobes, 30 cd	N/A	Y
	EG1-V60, EG1R-V60, EG1F-V60, EG1RF-V60, G1-V60, G1R-V60, G1F-V60, G1RF-V60, MG1-V60, MG1R-V60, MG1F-V60, MG1RF-V60	Genesis strobes, 60 cd	N/A	Y
	EG1-V75, EG1R-V75, EG1F-V75, EG1RF-V75, G1-V75, G1R-V75, G1F-V75, G1RF-V75, MG1-V75, MG1R-V75, MG1F-V75, MG1RF-V75	Genesis strobes, 75 cd	N/A	Y
	EG1-V110, EG1R-V110, EG1F-V110, EG1RF-V110, G1-V110, G1R-V110, G1F-V110, G1RF-V110, MG1-V110, MG1R-V110, MG1F-V110, MG1RF-V110	Genesis strobes, 110 cd	N/A	Y
	EG1-HV15, EG1R-HV15, G1-HV15, G1R-HV15, MG1-HV15, MG1R-HV15	Genesis temporal horn/strobes, low dbA, 15 cd	Y	Y
	EG1-HV30, EG1R-HV30, G1-HV30, G1R-HV30, MG1-HV30, MG1R-HV30	Genesis temporal horn/strobes, low dbA, 30 cd	Y	Y
	EG1-HV60, EG1R-HV60, G1-HV60, G1R-HV60, MG1-HV60, MG1R-HV60	Genesis temporal horn/strobes, low dbA, 60 cd	Y	Y
	EG1-HV75, EG1R-HV75, G1-HV75, G1R-HV75, MG1-HV75, MG1R-HV75	Genesis temporal horn/strobes, low dbA, 75 cd	Y	Y
	EG1-HOV15, EG1R-HOV15, EG1F-HOV15, EG1RF-HOV15, G1-HOV15, G1R-HOV15, G1F-HOV15, G1RF-HOV15, MG1-HOV15, MG1R-HOV15, MG1F-HOV15, MG1RF-HOV15	Genesis temporal horn/strobes, high dbA, 15 cd	Y	Y
	EG1-HOV30, EG1R-HOV30, EG1F-HOV30, EG1RF-HOV30, G1-HOV30, G1R-HOV30, G1F-HOV30, G1RF-HOV30, MG1-HOV30, MG1R-HOV30, MG1F-HOV30, MG1RF-HOV30	Genesis temporal horn/strobes, high dbA, 30 cd	Y	Y
	EG1-HOV60, EG1R-HOV60, EG1F-HOV60, EG1RF-HOV60, G1-HOV60, G1R-HOV60, G1F-HOV60, G1RF-HOV60, MG1-HOV60, MG1R-HOV60, MG1F-HOV60, MG1RF-HOV60	Genesis temporal horn/strobes, high dbA, 60 cd	Y	Y
	EG1-HOV75, EG1R-HOV75, EG1F-HOV75, EG1RF-HOV75, G1-HOV75, G1R-HOV75, G1F-HOV75, G1RF-HOV75, MG1-HOV75, MG1R-HOV75, MG1F-HOV75, MG1RF-HOV75	Genesis temporal horn/strobes, high dbA, 75 cd	Y	Y
	EG1-HOV110, EG1R-HOV110, EG1F-HOV110, EG1RF-HOV110, G1-HOV110, G1R-HOV110, G1F-HOV110, G1RF-HOV110, MG1-HOV110, MG1R-HOV110, MG1F-HOV110, MG1RF-HOV110	Genesis temporal horn/strobes, high dbA, 110 cd	Y	Y
	EG1-HOV110R, G1-HOV110R, MG1-HOV110R	Genesis temporal horn/strobe, 52 cd, private mode only	Y	Y
	EG1-P, EG1R-P, EG1F-P, EG1RF-P, G1-P, G1R-P, G1F-P, G1RF-P, MG1-P, MG1R-P, MG1F-P, MG1RF-P	Genesis horns	Y	

Manufacturer	Model	Description	Audible sync	Visible sync
	EG1-VM, EG1R-VM, EG1F-VM, EG1RF-VM, G1-VM, G1R-VM, G1F-VM, G1RF-VM, MG1-VM, MG1R-VM, MG1F-VM, MG1RF-VM	Genesis strobes, 15 to 110 cd	N/A	Y
	EG1-C, EG1R-C, EG1F-C, EG1RF-C, G1-C, G1R-C, G1F-C, G1RF-C, MG1-C, MG1R-C, MG1F-C, MG1RF-C	Genesis chimes	N/A	N/A
	EG1-CVM, EG1R-CVM, EG1F-CVM, EG1RF-CVM, G1-CVM, G1R-CVM, G1F-CVM, G1RF-CVM, MG1-CVM, MG1R-CVM, MG1F-CVM, MG1RF-CVM	Genesis chime/strobes, 15 to 110 cd	N/A	Y
	EGC-VM, EGCF-VM, EGCRF-VM, GC-VM, GCF-VM, MGC-VM, MGCF-VM, MGCRF-VM	Genesis ceiling strobes, 15 to 95 cd	N/A	Y
	EGC-VMH, EGCF-VMH, GC-VMH, GCF-VMH, MGC-VMH, MGCF-VMH	Genesis ceiling strobes, 95 to 177 cd	N/A	Y
	EGC-S2VM, EGCF-S2VM, GC-S2VM, GCF-S2VM, MGC-S2VM, MGCF-S2VM	Genesis ceiling speaker/strobe, 25 VRMS, 15 to 95 cd	N/A	Y
	EGC-S7VM, EGCF-S7VM, GC-S7VM, GCF-S7VM, MGC-S7VM, MGCF-S7VM	Genesis ceiling speaker/strobe, 70 VRMS, 15 to 95 cd	N/A	Y
	EGC-S2VMH, EGCF-S2VMH, GC-S2VMH, GCF-S2VMH, MGC-S2VMH, MGCF-S2VMH	Genesis ceiling speaker/strobe, 25 VRMS, 95 to 177 cd	N/A	Y
	EGC-S7VMH, EGCF-S7VMH, GC-S7VMH, GCF-S7VMH, MGC-S7VMH, MGCF-S7VMH	Genesis ceiling speaker/strobe, 70 VRMS, 95 to 177 cd	N/A	Y
	EGC-HDVM, EGCF-HDVM, EGCRF-HDVM, GC-HDVM, GCF-HDVM, MGC-HDVM, MGCF-HDVM, MGCRF-HDVM	Genesis ceiling horn/strobe, 15 to 95 cd	Y	Y
	EGC-HDVMH, EGCF-HDVMH, GC-HDVMH, GCF-HDVMH, MGC-HDVMH, MGCF-HDVMH	Genesis ceiling horn/strobe, 95 to 177 cd	Y	Y
	EG4-S2VM, EG4R-S2VM, EG4F-S2VM, EG4RF-S2VM, G4-S2VM, G4R-S2VM, G4F-S2VM, G4RF-S2VM, MG4-S2VM, MG4R-S2VM, MG4F-S2VM, MG4RF-S2VM	Genesis speaker/strobe, 25 VRMS, 15 to 110 cd	N/A	Y
	EG4-S7VM, EG4R-S7VM, EG4F-S7VM, EG4RF-S7VM, G4-S7VM, G4R-S7VM, G4F-S7VM, G4RF-S7VM, MG4-S7VM, MG4R-S7VM, MG4F-S7VM, MG4RF-S7VM	Genesis speaker/strobe, 70 VRMS, 15 to 110 cd	N/A	Y
	G4LFRF-H, G4LFRN-H, G4LFWF-H, G4LFWN-H	Genesis Low Frequency (520 Hz) horn, temporal or steady, low or high dB	Y	N/A
	G4LFRF-HVM, G4LFRN-HVM, G4LFWF-HVM, G4LFWN-HVM	Genesis Low Frequency (520 Hz) horn-strobe, temporal or steady, low or high dB, 15 to 110 cd	Y	Y
	WG4RF-SVMC, WG4RN-SVMC, WG4WA-SVMC, WG4WF-SVMC, WG4WN-SVMC	Outdoor Genesis speaker/strobe, 25/70 VRMS, 15/29/70/87 cd [1]	N/A	Y
	WG4RF-SVMHC, WG4RN-SVMHC, WG4WA-SVMHC, WG4WF-SVMHC, WG4WN-SVMHC	Outdoor Genesis speaker/strobe, 25/70 VRMS, 102/123/147/161 [1]	N/A	Y
	WG4RF-HVMC, WG4RN-HVMC, WG4WF-HVMC, WG4WN-HVMC	Outdoor Genesis horn/strobe, 15/29/70/87 cd [1]	Y	Y
	WG4RF-HVMHC, WG4RN-HVMHC, WG4WF-HVMHC, WG4WN-HVMHC	Outdoor Genesis horn/strobe, 102/123/147/161 cd [1]	Y	Y
	WG4RF-H, WG4WF-H, WG4RN-H, WG4WN-H	Outdoor Genesis horn [1]	Y	N

[1] When metallic conductors are installed that extend beyond one building, the circuits are *required* to be protected with UL 497B listed transient protectors with the appropriate voltage ratings for the circuit being protected. When notification appliances are installed outside of a building (e.g. mounted on an exterior wall) and are connected to an interior circuit that may not have transient protection, it is *recommended* that these circuits also be protected with UL 497B listed transient protection with the appropriate voltage ratings for the circuit being protected. Consult applicable codes for further information.

Accessories

Manufacturer	Model	Description	
Edwards	6254A-003	Auxiliary relay	
	CTM	City tie module	
	E-RLCD	Remote LCD annunciator, acknowledge/silence and lamp test buttons, white, English	
	E-RLCD-C	Remote LCD annunciator, common controls, white, English	
	E-RLED-C	Remote LED annunciator, 16 zones, common controls, white, English	
	GCI	Graphic annunciator driver card	
	GCIX	GCI expander card	
	MR-101/C, MR-101/T	Single multivoltage control relay module, SPDT	
	MR-104/C, MR-104/T	Four multivoltage control relay module, SPDT	
	MR-201/C, MR-201/T	Single multivoltage control relay module, DPDT	
	MR-204/C, MR-204/T	Four multivoltage control relay module, DPDT	
	PAM-1	Multivoltage control relay	
	PT-1S, MIR-PRT/S	System event printer (serial)	
	RA-ENC1	Annunciator cabinet, surface mount, holds one remote annunciator	
	RA-ENC2	Annunciator cabinet, surface mount, holds one remote annunciator and one remote expander	
	RA-ENC3	Annunciator cabinet, surface mount, holds one remote annunciator and two remote expanders	
	RKEY	Remote annunciator enable key switch	
	RLCD(F)	Remote LCD annunciator, acknowledge/silence and lamp test buttons, white, English (French)	
	RLCD-C(F)	Remote LCD annunciator, common controls, white, English (French)	
	RLCD-CR	Remote LCD annunciator, common controls, red, English	
	RLCD-R	Remote LCD annunciator, acknowledge/silence and lamp test buttons, red, English	
	R-LED	Remote alarm LED indicator	
	RLED24(R)	Remote LED annunciator, 24 zones, white (red)	
	RLED-C(F)	Remote LED annunciator, 16 zones, common controls, white, English (French)	
	RLED-CR	Remote LED annunciator, 16 zones, common controls, red, English	
	RPM	Reverse polarity module	
	Gentex	AVSM-R [1]	Synchronization control module, red
		AVSM-W [1]	Synchronization control module, white
	System Sensor	MDL3 [1]	Synchronization control module
	Wheelock	DSM-12/24-R [1]	Synchronization control module, red

[1] Synchronization is limited to a single circuit.

External power supplies

Manufacturer	Model	Description
Edwards	BPS6A, EBPS6A, MIRBPS6A	Booster power supply, 6.5 A, 120 V, 50/60 Hz
	BPS6A/230, EBPS6A/230, MIRBPS6A/230	Booster power supply, 6.5 A, 230 V, 50/60 Hz
	BPS6AC	Booster power supply, 6.5 A, 120 V, 50/60 Hz
	BPS6CAA	Booster power supply, 6.5 A, 120 V, 50/60 Hz (California)
	BPS10A, EBPS10A, MIRBPS10A	Booster power supply, 10 A, 120 V, 50/60 Hz
	BPS10A/230, EBPS10A/230, MIRBPS10A/230	Booster power supply, 10 A, 230 V, 50/60 Hz
	BPS10AC	Booster power supply, 10 A, 120 V, 50/60 Hz
	BPS10CAA	Booster power supply, 10 A, 120 V, 50/60 Hz (California)
	EAPS6A, APS6A	Auxiliary power supply, 6.5 A, 120 V, 50/60 Hz
	EAPS6A/230, APS6A/230	Auxiliary power supply, 6.5 A, 230 V, 50/60 Hz
	EAPS10A, APS10A	Auxiliary power supply, 10 A, 120 V, 50/60 Hz
	EAPS10A/230, APS10A/230	Auxiliary power supply, 10 A, 230 V, 50/60 Hz

CMS receivers

Manufacturer	Model	Format
Ademco	685	Contact ID
FBII	CP220	Contact ID
Osborne-Hoffman	OH 2000E	Contact ID, TCP/IP
Radionics	D6600	Contact ID
Sur-Gard	SG-MLR1 and MLR2	Contact ID
MCDI	TLR and TLR+	Contact ID

Contact information

For contact information, see www.edwardssignaling.com.

© 2015 UTC Fire & Security Americas Corporation, Inc. All rights reserved.